

# NE Series

NE Series specifications

neWR-5 / WR-5 Wall Remote Controls

PRELIMINARY



Remote control your system from any location. The neWR-5 & WR-5 wall remote controls fit in standard wall boxes. White faceplates can be covered with a standard decora plate (not included). Both devices have two Up/Down buttons for volume level, preset selection, etc. A two-character alphanumeric display gives the operator a visual indication that verifies the desired changes have been accepted by the system. Six programmable function select buttons with LEDs can each be programmed for one of the following functions:

Preset Recall – Immediately recall an assigned preset.

Preset Scroll – Allows user to select any of the allowed presets via the up/down arrow button shown by the alphanumeric display.

Gain Control – Allows volume control of assigned inputs/matrix mix/outputs.

Channel Mute – Allows mute control of assigned inputs/outputs.

Zone Source Selection – Allows for on/off control of assigned inputs, but only for a specific output.

Logic High or Low for the ne24.24M processor

The **neWR-5** is a programmable ethernet based remote control unit for Ashly NE Series products. Connecting and powering the neWR-5 is done using standard Cat-5 ethernet cable and an IEEE 802.3af Power over Ethernet (PoE) switch, hub, or inline injector (purchased separately). If PoE is not available, a 15-48VDC power supply can be hardwired directly to each unit (2 watts needed per unit). A hardwired Lock-Out feature on the neWR-5 will render all buttons inactive.

The **WR-5** is a microprocessor based remote control unit for Ashly NE Series products using a four conductor serial bus. Up to four WR-5 units can be daisy-chained and powered from the host product. More WR-5 units can be added by using an Ashly RPS-18 inline power supply adapter. *The RD-8C can not be used with the WR-5.*

A European version of the WR-5 is available

**WR-5e**



## Features:

- Remote Control for your system
- Visual indication verifies changes
- Preset Recall
- Preset Scroll
- Input Gain Control
- Matrix Mix Gain Control
- Output Gain Control
- Channel Mute
- Zone Source Select
- Logic High/Low (ne24.24M)
- Lock-Out Feature (neWR-5)
- Microprocessor = 4-wire cable (WR-5)
- Ethernet = Cat-5 cable (neWR-5)

Ashly Audio, Inc.  
847 Holt Road  
Webster, New York USA 14580-9103  
P: 800-828-6308, +1-585-872-0010  
F: +1-585-872-0739  
www.ashly.com info@ashly.com  
Specifications subject to change without prior notice.  
Latest information available at www.ashly.com.  
© 2011 Ashly Audio, Inc.  
Printed in U.S.A. 01/11

Visit [www.ashly.com](http://www.ashly.com) to download Protea NE software and data sheets